Effective February 2016 Supersedes August 2015

# BUSSMAN

# Low-Peak<sup>™</sup> LP-CC Class CC 600Vac/300Vdc, 1/2-30A time-delay fuses





Catalog numbers (amps)									
LP-CC-1/2	LP-CC-1-1/2	LP-CC-3	LP-CC-6	LP-CC-12					
LP-CC-6/10	LP-CC-1-6/10	LP-CC-3-2/10	LP-CC-6-1/4	LP-CC-15					
LP-CC-8/10	LP-CC-1-8/10	LP-CC-3-1/2	LP-CC-7	LP-CC-20					
LP-CC-1	LP-CC-2	LP-CC-4	LP-CC-7-1/2	LP-CC-25					
LP-CC-1-1/8	LP-CC-2-1/4	LP-CC-4-1/2	LP-CC-8	LP-CC-30					
LP-CC-1-1/4	LP-CC-2-1/2	LP-CC-5	LP-CC-9						
LP-CC-1-4/10	LP-CC-2-8/10	LP-CC-5-6/10	LP-CC-10						

## **Carton quantity:**

Amp rating	Carton qty.		
1/4-30	10		

(10.3mm)

## **Catalog symbol:**

LP-CC-(amp)

# **Description:**

Ultimate protection Class CC current-limiting, timedelay fuses. Time-delay – 12 seconds (minimum) at 200% of rated current.

# **Specifications:**

#### Ratings

- Volts
  - 600Vac,
  - 300Vdc (1/2-2-8/10A, 20-30A)
  - 150Vdc (3-15A)
- · Amps 1/2-30A
- IR
  - 200kA Vac RMS Sym. .
  - 20kA Vdc

#### Agency information

- UL® Listed Class CC, Std. 248-4, Guide JDDZ, File E4273
- CSA® Certified; Class 1422-02, File 53787
- CE
- RoHS compliant (20-30A)



#### **Features:** 200kA interrupting rating complies with NEC® Section 110.9 for today's large capacity

- systems. Fast short-circuit protection and dual-element.
- time-delay performance provide ultimate protection.
- Reduces existing fuse inventory by up to 33% when upgrading to Low-Peak fuses.
- Consistent 2:1 ampacity ratios for all Low-Peak fuses make selective coordination easy.
- Time-delay characteristic avoids unwanted fuse openings from surge currents while fast response speed under short-circuit conditions provides a high degree of current limitation.
- Current-limitation protects downstream components against damaging thermal and magnetic effects of short-circuit currents.
- · A superior, all-purpose, space-saving branch circuit fuse that meets most protection requirements up to 30A.
- Very compact, with a physical size only 13/32" x 1 1/2" (10.3 x 38.1mm) with rejction tip.
- Proper sizing can provide "no damage" Type 2 coordinated protection for NEMA and IEC motor controllers.
- Can be used where either a time-delay or a fast-acting fuse is needed, making selection easier and reducing spare fuse inventories for substantial cost reduction.
- Superior protection for small horsepower motor circuits.

#### **Dimensions - in (mm)** 0.41" (± 0.005) 1.5" (± 0.031)

(38.1mm)

# **Recommended fuse blocks and holders:**

Fuse amps	1-Pole	2-Pole	3-Pole						
Modular open blocks									
0-30	BCM603-1_	BCM603-2_	BCM603-3_						
DIN-Rail holders									
	CHCC1D_	CHCC2D_	CHCC3D_						
0-30	_	—	OPM-NG						
0-30	_	—	OPM-1038_						
	_	—	OPM-1038_SW						
Panel mount holders									
0.20	HPS	—	_						
0-30	HPF	—	_						
In-line holders									
0.20	_	HEY	_						
0-30	HEZ	_	_						

For additional information on Class CC fuse blocks and holders, see data sheets:

- Modular open blocks # 10241 (BCM)
- DIN-Rail holders No. 3185 (CHCC), No. 1109 (OPM), No. 1102 (OPM-1038), No. 1103 (OPM-1038\_SW)
- · Panel mount holders No. 2113 (HPS), No. 2114 (HPF)
- · In-line holders No. 2126 (HEY), No. 2130 (HEZ)

# Time-current curves - average melt:



# **Current-limitation curves:**



Current-limiting effects:

Prospective	Let-through current (apparent RMS symmetrical vs. fuse rating)					
S.C.C.	1-1/4A	2-8⁄10A	15A	20A	25A	30A
1000	100	135	240	305	380	435
3000	140	210	350	440	575	580
5000	165	255	420	570	690	710
10,000	210	340	540	700	870	1000
20,000	260	435	680	870	1090	1305
30,000	290	525	800	1030	1300	1520
40,000	315	610	870	1150	1390	1700
50,000	340	650	915	1215	1520	1820
60,000	350	735	1050	1300	1650	1980
80,000	390	785	1130	1500	1780	2180
100,000	420	830	1210	1600	2000	2400
200,000	525	1100	1600	2000	2520	3050

NOTE: To calculate  $I_p$  ( $I_{peak}$ ) multiply  $I_{RMS}$  value by 2.3.

The only controlled copy of this data sheet is the electronic read-only version located on the Eaton network drive. All other copies of this document are by definition uncontrolled. This bulletin is intended to clearly present comprehensive product data and provide technical information that will help the end user with design applications. Eaton reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Eaton also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.

Eaton 1000 Eaton Boulevard Cleveland, OH 44122 Eaton.com

Bussmann Division 114 Old State Road Ellisville, MO 63021 United States Eaton.com/bussmannseries

© 2016 Eaton All Rights Reserved Printed in USA Publication No. 1023 - BU-SB13732 February 2016

Eaton, Bussmann and Low-Peak are valuable trademarks of Eaton in the US and other countries. You are not permitted to use the Eaton trademarks without prior written consent of Eaton.

UL is a registered trademark of the Underwriters Laboratories, Inc. CSA is a registered trademark of the Canadian Standards Group. NEC is a registered trademark of the National Fire Protection Association, Inc.

For Eaton's Bussmann series product information, call 1-855-287-7626 or visit: Eaton.com/bussmannseries

Follow us on social media to get the latest product and support information.



