

# Eaton EFS3190

Catalog Number: EFS3190

Eaton Crouse-Hinds series EFS pushbutton control station, With pushbuttons, With one 1" hub, Feraloy iron alloy, Two circuit universal, 2, 2, Single-gang, 2, Dead end, 1", 600 Vac

## General specifications

Product Name	Catalog Number
Eaton Crouse-Hinds series EFS pushbutton control station	EFS3190
	UPC
	782274285702
Product Length/Depth	Product Height
3.5 in	5.91 in
Product Width	Product Weight
5.25 in	8.4 lb

## Certifications and compliances

### Area classification

Hazardous/Classified Locations

### Standards type

NEC/CEC

### NEC hazardous rating

Class I, Division 1

Class I, Division 2

Class II, Division 1

Class II, Division 2

Class III

### NEMA Rating

3

7

9

## Product specifications

### Enclosure type

With pushbuttons

### Voltage rating

600 Vac

### Number of gangs

Single-gang

### Number of pushbuttons

2

### Number of devices

2

### Normal position

Two circuit universal

### Style

Dead end

### Trade size

1"

### Number of circuits

2

### Hub style

With one 1" hub

### Material

Feraloy iron alloy

## Resources

### 3D models

[SP3D Design Package - EDS and EFS Explosionproof Control Stations](#)

### Catalogs

[EFS explosionproof control stations for group B applications - catalog page](#)

### Certification reports

[EDS and EFS Explosionproof Pushbutton, Pilot Light, and Selector Switch Control Stations UL certification](#)

[EDS and EFS Explosionproof Pushbutton, Pilot Light, and Selector Switch Control Stations Canadian certification](#)

### Installation instructions

IF 899 - EDSX, EDS, EFS, DSDX and DSD Control Stations

IF 328 - EDS, EFS, EDSC and EFSC Single- and Two-gang Device Bodies

Specifications and datasheets

Eaton Specification Sheet - EFS3190



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)